

EUC-M

EUC-026SxxxSVM BIS

| | 1 | | | 2 | | | 3 |
|--------|--------------|-------------|------|-------|--------|--------|--------------------|
| | | | | | 120Vac | 220Vac | |
| 350 mA | 90 ~ 305 Vac | 37 ~ 74 Vdc | 26 W | 88.5% | 0.99 | 0.96 | EUC-026S050SVM3003 |
| 700 mA | 90 ~ 305 Vac | 20 ~ 37 Vdc | 26 W | 87.0% | 0.99 | 0.96 | EUC-026S070SVM3000 |

- 1 : 120-240 Vac
 2 220 Vac
 3 SELV BIS

EUC-035SxxxSVM BIS

| | 1 | | | 2 | | | 3 |
|---------|--------------|-----------|------|-------|--------|--------|--------------------|
| | | | | | 120Vac | 220Vac | |
| 600 mA | 90 ~ 305 Vac | 29~58 Vdc | 35 W | 88.0% | 0.99 | 0.96 | EUC-035S070SVM3002 |
| 700 mA | 90 ~ 305 Vac | 25~50 Vdc | 35 W | 87.0% | 0.99 | 0.96 | EUC-035S070SVM3000 |
| 900 mA | 90 ~ 305 Vac | 20~39 Vdc | 35 W | 86.5% | 0.99 | 0.96 | EUC-035S105SVM3003 |
| 1050 mA | 90 ~ 305 Vac | 18~33 Vdc | 35 W | 86.0% | 0.99 | 0.96 | EUC-035S105SVM3000 |

- 1 : 120-240 Vac
 2 220 Vac
 3 SELV BIS

EUC-060SxxxSVM BIS

| | 1 | | | 2 | | | 3 |
|---------|--------------|--------------|------|-------|--------|--------|-----------------------------------|
| | | | | | 120Vac | 220Vac | |
| 500 mA | 90 ~ 305 Vac | 60 ~ 120 Vdc | 60 W | 90.0% | 0.99 | 0.96 | EUC-060S070SVM3004 |
| 550 mA | 90 ~ 305 Vac | 54 ~ 109 Vdc | 60 W | 90.5% | 0.99 | 0.96 | EUC-060S070SVM3003 |
| 600 mA | 90 ~ 305 Vac | 50 ~ 100 Vdc | 60 W | 90.5% | 0.99 | 0.96 | EUC-060S070SVM3002 |
| 650 mA | 90 ~ 305 Vac | 48 ~ 92 Vdc | 60 W | 91.5% | 0.99 | 0.96 | EUC-060S070SVM3001 |
| 700 mA | 90 ~ 305 Vac | 48 ~ 86 Vdc | 60 W | 89.0% | 0.99 | 0.96 | EUC-060S070SVM3000 |
| 1050 mA | 90 ~ 305 Vac | 34 ~ 57 Vdc | 60 W | 89.0% | 0.99 | 0.96 | EUC-060S105SVM3000 ⁽⁴⁾ |
| 1200 mA | 90 ~ 305 Vac | 25 ~ 50 Vdc | 60 W | 89.0% | 0.99 | 0.96 | EUC-060S180SVM3006 ⁽⁴⁾ |
| 1500 mA | 90 ~ 305 Vac | 20 ~ 40 Vdc | 60 W | 87.0% | 0.99 | 0.96 | EUC-060S180SVM3003 ⁽⁴⁾ |
| 1600 mA | 90 ~ 305 Vac | 20 ~ 38 Vdc | 60 W | 87.0% | 0.99 | 0.96 | EUC-060S180SVM3002 ⁽⁴⁾ |
| 1800 mA | 90 ~ 305 Vac | 20 ~ 33 Vdc | 60 W | 87.0% | 0.99 | 0.96 | EUC-060S180SVM3000 ⁽⁴⁾ |

- 1 : 120-240 Vac
 2 220 Vac

- 3 BIS
- 4 SELV

EUC-060SxxxDVM BIS

| | 1 | | | 2 | | | 3 |
|--------|-------------------------------|--------------|------|-------|--------|--------|--------------------|
| | | | | | 120Vac | 220Vac | |
| 500 mA | 90 ~ 305 Vac 127 ~ 250 Vdc | 60 ~ 120 Vdc | 60W | 90.0% | 0.99 | 0.96 | EUC-060S070DVM3004 |
| 550 mA | 90 ~ 305 Vac 127 ~ 250 Vdc | 54 ~ 109 Vdc | 60 W | 89.0% | 0.99 | 0.96 | EUC-060S070DVM3003 |
| 600 mA | 90 ~ 305 Vac 127 ~ 250 Vdc | 50 ~ 100 Vdc | 60 W | 89.0% | 0.99 | 0.96 | EUC-060S070DVM3002 |
| 650 mA | 90 ~ 305 Vac 127 ~ 250 Vdc | 48 ~ 92 Vdc | 60 W | 89.0% | 0.99 | 0.96 | EUC-060S070DVM3001 |
| 700 mA | 90 ~ 305 Vac 127 ~ 250 Vdc | 48 ~ 86 Vdc | 60W | 89.0% | 0.99 | 0.96 | EUC-060S070DVM3000 |

- 1 : 120-240 Vac/127-250Vdc
- 2 220 Vac
- 3 BIS

EDC

EDC-075SxxxSV BIS

| | 1 | 2 | | 3 | 3 | 4 |
|---------|---------------|--------------|------|-------|------|--------------------|
| 700 mA | 140 ~ 305 Vac | 54 ~ 107 Vdc | 75 W | 90.5% | 0.96 | EDC-075S105SV-3007 |
| 750 mA | 140 ~ 305 Vac | 50 ~ 100 Vdc | 75 W | 90.5% | 0.96 | EDC-075S105SV-3006 |
| 800 mA | 140 ~ 305 Vac | 47 ~ 93 Vdc | 75 W | 91.0% | 0.96 | EDC-075S105SV-3005 |
| 860 mA | 140 ~ 305 Vac | 44 ~ 88 Vdc | 75 W | 90.5% | 0.96 | EDC-075S105SV-3004 |
| 900 mA | 140 ~ 305 Vac | 42 ~ 83 Vdc | 75 W | 91.0% | 0.96 | EDC-075S105SV-3003 |
| 950 mA | 140 ~ 305 Vac | 40 ~ 79 Vdc | 75 W | 90.0% | 0.96 | EDC-075S105SV-3002 |
| 1000 mA | 140 ~ 305 Vac | 36 ~ 75Vdc | 75 W | 90.5% | 0.96 | EDC-075S105SV-3001 |
| 1050 mA | 140 ~ 305 Vac | 36 ~ 71 Vdc | 75 W | 90.0% | 0.96 | EDC-075S105SV-3000 |

- 1 : 220-240Vac
- 2 100-305Vac 100-140Vac
- 3 220 Vac
- 4 BIS

EDC-100SxxxSV BIS

| | 1 | 2 | | | 3 | 3 | 4 |
|---------|---------------|---|--------------|-------|-------|------|--------------------|
| 700 mA | 140 ~ 305 Vac | | 71 ~ 143 Vdc | 100 W | 91.0% | 0.96 | EDC-100S105SV-3007 |
| 750 mA | 140 ~ 305 Vac | | 66 ~ 133 Vdc | 100 W | 89.5% | 0.96 | EDC-100S105SV-3006 |
| 800 mA | 140 ~ 305 Vac | | 62 ~ 125 Vdc | 100 W | 90.5% | 0.96 | EDC-100S105SV-3005 |
| 860 mA | 140 ~ 305 Vac | | 58 ~ 116 Vdc | 100 W | 90.5% | 0.96 | EDC-100S105SV-3004 |
| 900 mA | 140 ~ 305 Vac | | 55 ~ 111 Vdc | 100 W | 90.5% | 0.96 | EDC-100S105SV-3003 |
| 950 mA | 140 ~ 305 Vac | | 52 ~ 105 Vdc | 100 W | 90.5% | 0.96 | EDC-100S105SV-3002 |
| 1000 mA | 140 ~ 305 Vac | | 50 ~ 100 Vdc | 100 W | 90.0% | 0.96 | EDC-100S105SV-3001 |
| 1050 mA | 140 ~ 305 Vac | | 47 ~ 95 Vdc | 100 W | 90.0% | 0.96 | EDC-100S105SV-3000 |

- 1 : 220-240Vac
- 2 100-305Vac 100-140Vac
- 3 220 Vac
- 4 BIS

EDC-150SxxxSV BIS

| | 1 | 2 | | | 3 | 3 | 4 |
|---------|---------------|---|---------------|-------|-------|------|--------------------|
| 700 mA | 140 ~ 305 Vac | | 107 ~ 214 Vdc | 150 W | 92.0% | 0.96 | EDC-150S105SV-3007 |
| 750 mA | 140 ~ 305 Vac | | 100 ~ 200 Vdc | 150 W | 92.0% | 0.96 | EDC-150S105SV-3006 |
| 800 mA | 140 ~ 305 Vac | | 97 ~ 187 Vdc | 150 W | 92.0% | 0.96 | EDC-150S105SV-3005 |
| 860 mA | 140 ~ 305 Vac | | 97 ~ 174 Vdc | 150 W | 92.0% | 0.96 | EDC-150S105SV-3004 |
| 900 mA | 140 ~ 305 Vac | | 97 ~ 166 Vdc | 150 W | 92.0% | 0.96 | EDC-150S105SV-3003 |
| 950 mA | 140 ~ 305 Vac | | 97 ~ 158 Vdc | 150 W | 92.0% | 0.96 | EDC-150S105SV-3002 |
| 1000 mA | 140 ~ 305 Vac | | 97 ~ 150 Vdc | 150 W | 91.5% | 0.96 | EDC-150S105SV-3001 |
| 1050 mA | 140 ~ 305 Vac | | 97 ~ 143 Vdc | 150 W | 91.0% | 0.96 | EDC-150S105SV-3000 |

- 1 : 220-240Vac
- 2 100-305Vac 100-140Vac
- 3 220 Vac
- 4 BIS

INVENTRONICS

BIS Models List

Rev. B

| 2019-04-16 | A | | / | / |
|------------|---|--------------------|---|---|
| 2021-02-24 | B | EUC-06OS180SVM3006 | / | |